

**PRODUCT**

# ESD Sole Grounder



**FEATURES**

- Hook and loop type with D Ring for size adjustment
- Double layers, conductive cup
- 3/4" Black hook and loop
- 2 pcs D-Ring
- 3/4" Elastic Strap

Open the buckle and hook and loop straps. Place the sole grounder on the bottom of the shoe. Close the toe strap by feeding the velcro through the plastic ring. Close the ankle strap. Place the ribbon inside the sock or shoe.

**SPECIFICATIONS**

DETAILS	TYPICAL VALUE
Outer conductive surface (black)	10 <sup>3</sup> - 10 <sup>5</sup> Ohms
Inner antistatic surface (ivory)	10 <sup>7</sup> - 10 <sup>8</sup> Ohms
Conductive tab	10 <sup>3</sup> - 10 <sup>4</sup> Ohms
Resistance	1Meg Resistor Built in

PRODUCT CODE	DESCRIPTION	SIZE (in)	NOTES
068-0020	ESD Sole Grounder	Small (6.3 x 6.6)	Each
068-0021	ESD Sole Grounder	Medium (6.5 x 7.3)	Each
068-0022	ESD Sole Grounder	Large (6.7 x 8.3)	Each
068-0023	ESD Sole Grounder	X Large (6.9 x 9.0)	Each

To request a quotation or for more information, please call **+1 512-580-4220**  
email [sales@antistat.com](mailto:sales@antistat.com) or visit [www.antistat.com](http://www.antistat.com)

IMPORTANT: This data sheet and its contents (the "Information") belong to Antistat or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but Antistat assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where Antistat was aware of the possibility of such loss or damage arising) is excluded. © 2021 Antistat.